

## Order Information

### Item

|            |  |
|------------|--|
| V130-33-T2 | PLC with Classic panel, Monochrome display 2.4"  |
| V130-J-T2  | PLC with Flat panel, Monochrome display 2.4"     |
| V350-35-T2 | PLC with Classic panel, Color touch display 3.5" |
| V350-J-T2  | PLC with Flat panel, Color touch display 3.5"    |
| V430-J-T2  | PLC with Flat panel, Color touch display 4.3"    |

You can find additional information, such as wiring diagrams, in the product's installation guide located in the Technical Library at [www.unitronics.com](http://www.unitronics.com).

## Power Supply

| Item                     | V130-T2<br>V130J-T2                          | V350-T2<br>V350J-T2 | V430J-T2    |
|--------------------------|--|---------------------|-------------|
| Input voltage            | 24VDC  |                     |             |
| Permissible range        | 20.4VDC to 28.8VDC with less than 10% ripple |                     |             |
| Max. current consumption | See Note 1                                   |                     |             |
| npn inputs               | 210mA@24VDC                                  | 230mA@24VDC         | 230mA@24VDC |
| pnp inputs               | 110mA@24VDC                                  | 135mA@24VDC         | 135mA@24VDC |

### Notes:

- To calculate the actual power consumption, subtract the current for each unused element from the maximum current consumption value according to the values below:

|              | Backlight | Ethernet card |
|--------------|-----------|---------------|
| V130/J       | 10mA      | 35mA          |
| V350/J/V430J | 20mA      | 35mA          |

## Digital Inputs

|                       |  |
|-----------------------|--|
| Number of inputs      | 12. See note 2                                       |
| Input type            | See note 2   |
| Galvanic isolation    | None   |
| Nominal input voltage | 24VDC  |
| Input Voltage         |  |
| pnp (source)          | 0-5VDC for Logic '0'<br>17-28.8VDC for Logic '1'     |
| npn (sink)            | 17-28.8VDC for Logic '0'<br>0-5VDC for Logic '1'     |
| Input Current         | 8mA@24VDC  |
| Input impedance       | 3K $\Omega$  |
| Response Time         | 10ms typical, when used as normal digital input      |
| Input Cable length    |  |
| Normal digital Input  | Up to 100 meters                                     |
| High Speed Input      | Up to 50 meters, shielded, see Frequency table below |

## High speed inputs

Specifications below apply when wired as HSC/shaft-encoder.  
See Note 2

| Frequency (max)     |        | See Note 3    |  |
|---------------------|--------|---------------|--|
| Cable length (max.) | HSC    | Shaft-encoder |  |
| 10m                 | 30kHz  | 20kHz         |  |
| 25m                 | 30kHz  | 13kHz         |  |
| 50m                 | 25kHz  | 9kHz          |  |
| Duty cycle          | 40-60% |               |  |
| Resolution          | 32-bit |               |  |

**Notes:**

2. V130/V350/V130J/V350J/V430J-T2 models comprise a total of 12 inputs.

12 inputs may be used as digital inputs. They may be wired, in a group, and set to either npn or pnp via a single jumper.

In addition, according to jumper settings and appropriate wiring:

- Inputs 10 and 11 can function as either digital or analog inputs.
- Inputs 0, 2, and 4 can function as high-speed counters, as part of a shaft-encoder, or as normal digital inputs.
- Inputs 1, 3, and 5 can function as either counter reset, as part of a shaft-encoder, or as normal digital inputs.
- If inputs 0, 2, 4 are set as high-speed counters (without reset), inputs 1, 3, 5 can function as normal digital inputs.

3. pnp/npn maximum frequency is at 24VDC.

**Analog Inputs**

|                            |  |         |
|----------------------------|--|---------|
| Number of inputs           | 2, according to wiring as described above in Note 2                                    |         |
| Input type                 | Multi-range inputs: 0-10V, 0-20mA, 4-20mA  |         |
| Input range                | 0-20mA, 4-20mA   | 0-10VDC |
| Input impedance            | 243Ω   | >150KΩ  |
| Maximum input rating       | 25mA, 6V   | 15V     |
| Galvanic isolation         | None   |         |
| Conversion method          | Successive approximation   |         |
| Resolution (except 4-20mA) | 10-bit (1024 units)  |         |
| Resolution (at 4-20mA)     | 204 to 1023 (820 units)  |         |
| Conversion time            | One configured input is updated per scan. See Note 4                                   |         |
| Precision                  | 0.9%   |         |
| Status indication          | Yes – if an analog input deviates above the permissible range, its value will be 1024. |         |

**Notes:**

4. For example, if 2 inputs are configured as analog, it takes 2 scans to update all analog values.

## Digital Outputs

|                                    |  |
|------------------------------------|--|
| Number of outputs                  | 12 transistor pnp (source)                             |
| Output type                        | P-MOSFET (open drain)                                  |
| Isolation                          | None   |
| Output current<br>(resistive load) | 0.5A maximum per output<br>3A maximum total per common |
| Maximum frequency                  | 50Hz (resistive load)<br>0.5Hz (inductive load)        |
| PWM maximum frequency              | 0.5KHz (resistive load). See Note 5                    |
| Short circuit protection           | Yes  |
| Short circuit indication           | Via software   |
| On voltage drop                    | 0.5VDC maximum   |
| Power supply for outputs           |  |
| Operating voltage                  | 20.4 to 28.8VDC  |
| Nominal voltage                    | 24VDC  |

### Notes:

5. Outputs 0 to 6 can be used as PWM outputs.

## Graphic Display Screen

| Item                      | V130-T2<br>V130J-T2   | V350-T2<br>V350J-T2   | V430J-T2          |
|---------------------------|---|---|-------------------|
| LCD Type                  | STN, LCD display  | TFT, LCD display  | TFT, LCD display  |
| Illumination backlight    | White LED   | White LED   | White LED         |
| Display resolution        | 128x64 pixels   | 320x240 pixels  | 480x272 pixels    |
| Viewing area              | 2.4"  | 3.5"  | 4.3"              |
| Colors                    | Monochrome  | 65,536 (16-bit)   | 65,536 (16-bit)   |
| Screen Contrast           | Via software<br>(Store value to SI 7,<br>values range: 0 to 100%) | Fixed   | Fixed             |
| Touchscreen               | None  | Resistive, analog   | Resistive, analog |
| 'Touch' indication        | None  | Via buzzer  | Via buzzer        |
| Screen brightness control | Via software<br>(Store value to SI 9,<br>0 = Off, 1 = On)         | Via software<br>(Store value to SI 9, values range: 0 to 100%)      |                   |
| Virtual Keypad            | None  | Displays virtual keyboard when the application requires data entry. |                   |

## Keypad

| Item           | V130-T2<br>V130J-T2   | V350-T2<br>V350J-T2  | V430J-T2 |
|----------------|---|--|----------|
| Number of keys | 20 keys, including 10 user-labeled keys   | 5 programmable function keys   |          |
| Key type       | Metal dome, sealed membrane switch  |  |          |
| Slides         | Slides may be installed in the operating panel faceplate to custom-label the keys. Refer to <i>V130 Keypad Slides.pdf</i> . A complete set of blank slides is available by separate order | Slides may be installed in the operating panel faceplate to custom-label the keys. Refer to <i>V350 Keypad Slides.pdf</i> . Two sets of slides are supplied with the controller: one set of arrow keys, and one blank set. | None     |

| <b>Program</b>      |  |   |                 |  |
|---------------------|--|---|-----------------|--|
| <b>Item</b>         | <b>V130-T2<br/>V130J-T2</b>  | <b>V350-T2<br/>V350J-T2</b>               | <b>V430J-T2</b> |  |
| Memory size         |  |   |                 |  |
| Application Logic   | 512KB  | 512KB                                     | 512KB           |  |
| Images              | 256KB  | 6MB                                       | 12MB            |  |
| Fonts               | 128KB  | 1MB                                       | 1MB             |  |
| <b>Operand type</b> | <b>Quantity</b>  |   | <b>Symbol</b>   | <b>Value</b>                                   |
| <b>Item</b>         | <b>V130-T2<br/>V130J-T2</b>  | <b>V350-T2<br/>V350J-T2<br/>V430J-T2</b>  |                 |  |
| Memory Bits         | 4096   | 8192                                      | MB              | Bit (coil)                                     |
| Memory Integers     | 2048   | 4096                                      | MI              | 16-bit signed/unsigned                         |
| Long Integers       | 256  | 512                                       | ML              | 32-bit signed/unsigned                         |
| Double Word         | 64   | 256                                       | DW              | 32-bit unsigned                                |
| Memory Floats       | 24   | 64  | MF              | 32-bit signed/unsigned                         |
| Fast Bits           | 1024   | 1024                                      | XB              | Fast Bits (coil) – not retained                |
| Fast Integers       | 512  | 512                                       | XI              | 16 bit signed/unsigned<br>(fast, not retained) |
| Fast Long Integers  | 256  | 256                                       | XL              | 32 bit signed/unsigned<br>(fast, not retained) |
| Fast Double Word    | 64   | 64  | XDW             | 32 bit unsigned (fast, not retained)           |
| Timers              | 192  | 384                                       | T               | Res. 10 ms; max 99h, 59 min, 59.99s            |
| Counters            | 24   | 32  | C               | 32-bit   |
| Data Tables         | 120K dynamic data (recipe parameters, datalogs, etc.)<br>192K fixed data (read-only data, ingredient names, etc)<br>Expandable via SD card. See Removable Memory below |   |                 |  |
| HMI displays        | Up to 1024   |   |                 |  |
| Program scan time   | 20µs per 1kb<br>of typical<br>application  | 15µs per 1kb<br>of typical<br>application |                 |  |

## Removable Memory

Micro SD card      Compatible with standard SD and SDHC; up to 32GB store datalogs, Alarms, Trends, Data Tables, backup Ladder, HMI, and OS.  
See Note 6

### Notes:

6. User must format via Unitronics SD tools utility.

---

## Communication Ports

|                                 |   |
|---------------------------------|---|
| Port 1                          | 1 channel, RS232/RS485 and USB device (V430 only). See Note 7 |
| Galvanic isolation              | No  |
| Baud rate                       | 300 to 115200 bps   |
| RS232                           |   |
| Input voltage                   | ±20VDC absolute maximum                                       |
| Cable length                    | 15m maximum (50')   |
| RS485                           |   |
| Input voltage                   | -7 to +12VDC differential maximum                             |
| Cable type                      | Shielded twisted pair, in compliance with EIA 485             |
| Cable length                    | 1200m maximum (4000')   |
| Nodes                           | Up to 32  |
| USB device ( <b>V430 only</b> ) |   |
| Port type                       | Mini-B, See Note 9  |
| Specification                   | USB 2.0 compliant; full speed                                 |
| Cable                           | USB 2.0 compliant; up to 3m                                   |
| Port 2 (optional)               | See Note 8  |
| CANbus (optional)               | See Note 8  |

### Notes:

- This model is supplied with a serial port: RS232/RS485 (Port 1). The standard is set to either RS232 or RS485 according to jumper settings. Refer to the product's Installation Guide.
- The user may order and install one or both of the following modules:
  - An additional port (Port 2). Available port types: RS232/RS485 isolated/non-isolated, Ethernet
  - A CANbus port
 Port module documentation is available on the Unitronics website.
- Note that physically connecting a PC to the controller via USB suspends RS232/RS485 communications via Port 1. When the PC is disconnected, RS232/RS485 resumes.

---

## I/O Expansion

|        |   |
|--------|---|
|        | Additional I/Os may be added. Configurations vary according to module.<br>Supports digital, high-speed, analog, weight and temperature measurement I/Os.  |
| Local  | Via I/O Expansion Port. Integrate up to 8 I/O Expansion Modules comprising up to 128 additional I/Os. Adapter required (P.N. EX-A2X).   |
| Remote | Via CANbus port. Connect up to 60 adapters to a distance of 1000 meters from controller; and up to 8 I/O expansion modules to each adapter (up to a total of 512 I/Os). Adapter required (P.N. EX-RC1). |

---

## Miscellaneous

|                     |   |
|---------------------|---|
| Clock (RTC)         | Real-time clock functions (date and time)   |
| Battery back-up     | 7 years typical at 25°C, battery back-up for RTC and system data, including variable data |
| Battery replacement | Yes. Coin-type 3V, lithium battery, CR2450  |

| <b>Dimensions</b> |        | <b>V130-T2</b>  | <b>V350-T2</b>  | <b>V430J-T2</b>   |
|-------------------|--------|---|---|---|
| <b>Item</b>       |        | <b>V130J-T2</b>   | <b>V350J-T2</b>   |   |
| Size              | Vxxx   | 109 x 114.1 x 68mm<br>(4.29 x 4.49 x 2.67").<br>See Note 10 | 109 x 114.1 x 68mm<br>(4.29 x 4.49 x 2.67").<br>See Note 10 |   |
|                   | Vxxx-J | 109 x 114.1 x 66mm<br>(4.92 x 4.49 x 2.59").<br>See Note 10 | 109 x 114.1 x 66mm<br>(4.92 x 4.49 x 2.59").<br>See Note 10 | 136 x 105.1 x 61.3mm<br>(5.35 x 4.13 x 2.41").<br>See Note 10 |
| Weight            |        | 315g (11.11 oz)   | 335g (11.81 oz)   | 365g (12.87 oz)   |

**Notes:**

10. For exact dimensions, refer to the product's Installation Guide.

**Environment**

|                         |  |
|-------------------------|--|
| Operational temperature | 0 to 50°C (32 to 122°F)  |
| Storage temperature     | -20 to 60°C (-4 to 140°F)  |
| Relative Humidity (RH)  | 10% to 95% (non-condensing)  |
| Mounting method         | Panel mounted (IP65/66/NEMA4X)<br>DIN-rail mounted (IP20/NEMA1)                            |
| Operating Altitude      | 2000m (6562 ft)  |
| Shock                   | IEC 60068-2-27, 15G, 11ms duration   |
| Vibration               | IEC 60068-2-6, 5Hz to 8.4Hz, 3.5mm constant amplitude,<br>8.4Hz to 150Hz, 1G acceleration. |

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the foregoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R'G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.

DOC13040-A0 01/15